PROCEEDING



2020 2nd International Conference on Industrial Electrical and Electronics (ICIEE) 20 – 21 October 2020



Department of Electrical Engineering UNIVERSITAS SULTAN AGENG TIRTAYASA

PROCEEDING

2020 2nd International Conference on **Industrial Electrical and Electronics (ICIEE)**

(ICIEE)

Virtual Conference 20 - 21 October 2020

Organizer: Department of Electrical Engineering Universitas Sultan Ageng Tirtayasa



Technical Co-Sponsor



Supported by:





PUI - PT KETAHANAN PANGAN (Inovasi Pangan Lokal)

Table of Contents

Cover	i
Copyright	iii
Foreword from General Chair	iv
Foreword from Rector Universitas Sultan Ageng Tirtayasa	v
Keynote Speakers' Profile	vi
Program Committee	ix
Organizing Committee	x
Parallel Session	xi
Table of Contents	xv
Author Index	xix
Life Assessment of Aluminium and Copper Winding Distribution Transformers Using Loss of Life Analysis	1
Zainal Arifin, Nugroho Adi, M. Herdy Ardiansah and Hastuti Aziz	
Study Operation Demonstration Project STT - PLN Of The Battery Energy Storage System In Buton Island (Baubau Southeast Sulawesi) Erlina Erlina, Heri Suyanto, Retno Aita Diantari and Tony Koerniawan	6
Analysis of Modelling and Engineering Building Power Integration System Based on Renewable Energy Frengky Panjaitan and Syamsir Abduh	11
Micro-Spatial Electricity Load Forecasting Using Clustering Technique Christine Widyastuti, Adri Senen and Oktaria Handayani	17
Feasibility Study for Development of Micro Grid System in Rural Island Mansur Mansur, Salama Manjang, Ardiaty Arief and Yusri Syam Akil	22
Transient Stability Analysis of a Hybrid Grid-Connected Battery-PV in Baubau Power System Heri Suyanto, Muhammad Hafidz and Ginas Alvianingsih	27
Control Strategy For Active Power Filter Based On P-Q Theory Under Non-Ideal Mains Voltages Moh. Jauhari, Abdillah Fashiha Ilman, Lin Prasetyani and Tresna Dewi	31
Techno Economic Modeling for Replacement of Diesel Power Plant Tyas Kartika Sari, Dianing Novita Nurmala Putri, Fajardhani, Syamsir Abduh, Maula Sukma Widjaja and Chairul Gagarin Irianto	36
Photovoltaic and Diesel Power Plant Optimization for Isolated Island Dianing Novita Nurmala Putri, Eddie Widiono Suwondo, Andrie Syatriawan, Syamsir Abduh, Ishak Kasim and Nazmia Kurniawati	41
Performance of Ground Mounted PV System Affected by Near Shadings Losses Handrea Bernando Tambunan, Andreas P Purnomoadi, Putu Agus Aditya Pramana, Brian Bramantyo SDA Harsono, Anindita Satria Surya and Achmad Syerif Habibie	46

Design of Multistage Fast Charging Strategy on Lead-Acid Batteries K.G.H Mangunkusumo, M. Ridwan, P.A.A Pramana and A.S Habibie	52
SCADA System Implementation for Small System Electricity Kemas M.Tofani, P. A. Permana, B. B. S. D. A Harsono, Dhandis R Jintaka and K. G. H Mangunnkusumo	57
Early warning and information on ultraviolet radiation (200-800 nm), Carbon monoxide gas and Temperature in open public areas using a microcontroller-based fuzzy logic method <i>Vector Anggit Pratomo, Gunady Haryanto, Adhi Mahendra and Agung Saputra</i>	62
Design of Prototype Measuring Motor Vehicles Velocity Using Hall Effect Sensor Series A- 1302 based On Arduino Mega2560 Muhammad Ifan Saputra, Sri Ratna Sulistiyanti, Sri Purwiyanti and Umi Murdika	66
Infusion Liquid Level Detection Tool Using IR Sensors and Photodiode Based on Microcontroller	70
Iswanto, Muhammad Sholeh Masnawan, Nia Maharani Raharja and Alfian Ma'arif	
Control of DC Motor Using Proportional Integral Derivative (PID): Arduino Hardware Implementation Alfian Ma'arif, Iswanto, Nia Maharani Raharja, Phisca Aditya Rosyady, Ahmad Raditya Cahya Baswara and Aninditya Anggari Nuryono	74
DC Motor Speed Control Based on Fuzzy Adaptive with Fuzzy Model Reference Learning Control (FMRLC) Algorithm <i>Masjudin, Alimuddin, Siti Nur Aisah and Romi Wiryadinata</i>	79
Nutrient Film Technique for Automatic Hydroponic System Based on Arduino Iswanto, Prisma Megantoro and Alfian Ma'arif	84
Growth of Yttria-Stabilized Zirconia Thin Layer on Silicon Wafer Substrate (100) Using Pulsed Laser Deposition <i>Agusutrisno, Abu Khalid Rivai, Edi Suharyadi, Mardiyanto and M. A. Shulhany</i>	87
Data Transmission and Storage of Local Meteorology Station in Hybrid Power Plant System (Photovoltaic and Wind Turbine) <i>Romi Wiryadinata, Citra Nurizati, Anggoro Suryo Pramudyo, Irma Saraswati and Sabah</i> <i>Benzeghda</i>	91
Cloud Classification from NOAA Satellite Image Using Learning Vector Quantization Method Ceri Ahendyarti, Romi Wiryadinata, Neneng Rohana and Fadil Muhammad	97
Automatic Cataract Classification System Using Neural Network Algorithm Backpropagation <i>Ri Munarto, Mochtar Ali Setyo Yudono and Endi Permata</i>	101
Detection of Hypoxic Symptoms System Based on Oxygen Saturation and Heart Rate Using Arduino Based Fuzzy Method Iswanto and Prisma Megantoro	107

Design of Automatic Headlight System Based on Road Contour and Beam from Other Headlights Fadil Muhammad, Dzulfiqar Dwi Yanto, Wahyuni Martiningsih, Vembi Noverli and Romi Wiryadinata	112
Utilization of Three-dimensional Spatial Maps in Access Point Placement Optimization A. Bayu Primawan	116
Evaluation of Implementation of The Use of Enterprise Resource Planning System In Service Company Priskila Christine Rahayu, Kornelius Feki Abednego and Rudy Vernando Silalahi	121
Optimization Of Sugeno Fuzzy Logic Based On Wireless Sensor Network In Forest Fire Monitoring System Setiyo Budiyanto, Lukman Medriavin Silalahi, Freddy Artadima Silaban, Ucuk Darusalam, Septi Andryana and Fajar Rahayu I. M	126
Towards Sustainable IoT Ecosystem Shafiq Ul Rehman, Parminder Singh, Selvakumar Manickam and Supriyanto Praptodiyono	135
Improved Learning Outcomes of Descriptive Statistics Through the Test Room and Data Processing Features in the Mobile Learning Model Susana Limanto, Fitri Dwi Kartikasari and Merlin Oeitheurisa	139
Heart Rate and Body Temperature Monitoring Based on Android Operating System Anna Nur Nazilah Chamim, Jalu Rinaldi, Yudhi Ardiyanto, Iswanto and Alfian Ma'arif	143
True Random Number Generator Based on Wake-Up Ring Oscillator Utilizing Post-Processing Optimization to Generate Random Bit Sequence Anang Adi Permana, Aprilia Kusuma Dewi and Magfirawaty	149
Design of Intelligent Decision Support System for Sugar Cane Supply Chains Based on Blockchain Technology Ratna Ekawati, Yandra Arkeman, Suprihatin and Titi Candra Sunarti	153
Comparison of Authentication Schemes on IoT Aulia Nurul Azizah, Fauzan Budi Setiawan and Magfirawaty	158
Integration of Firewall and IDS on Securing Mobile IPv6 Supriyanto Praptodiyono, Moh. Jauhari, Rian Fahrizal, Iznan H. Hasbullah, Azlan Osman and Shafiq Ul Rehman	163
Implementation Multipath Routing With Equal Cost Multipath (ECMP) and Per Connection Classifier (PCC) <i>Rian Fahrizal, Muhammad Iman Santoso and Muhammad Zainul Arifin</i>	169
Random Forest Regression for Predicting Metamaterial Antenna Parameters Nazmia Kurniawati, Dianing Novita Nurmala Putri and Yuli Kurnia Ningsih	174

Performance Evaluation of Body Temperature Data Transmission Using Turbo Codes in 4G- LTE	179
Damar Widjaja and Dimaz Damar Wisya Wicaksana	
Size Reduction of Multiple Feed Line Microstrip Antenna Using Peripheral Slit Technique Syah Alam, Lydia Sari, Indra Surjati, Rakesh, Yuli Kurnia Ningsih and Newton Onasie	183
5G NR Planning at Frequency 3.5 GHz : Study Case in Indonesia Industrial Area Rai Nur Esa, Alfin Hikmaturokhman and Achmad Rizal Danisya	187
Design of a Microstrip Antenna Dual Band Patch Rectangular Using a Combination Stub and Slit Methods For LTE and Wi-Fi Applications <i>Herudin, Anggoro Suryo Pramudyo and Teguh Firmansyah</i>	194
Performance Comparison of GPRS and LTE Telecommunication Network using OpenAirInterface and OpenBTS with USRP <i>Yeremia Nikanor Nugroho, Riri Fitri Sari and Ruki Harwahyu</i>	197
5G NR Planning at mmWave Frequency : Study Case in Indonesia Industrial Area Ghina Fahira, Alfin Hikmaturokhman and Achamd Rizal Danisya	205
Design of a Microstrip Antenna Array Dual Band Using Stub Method Herudin, Teguh Firmansyaha and Anggoro Suryo Pramudyo	211
Design of Array Microstrip Antenna 4x4 Element For Microwave Radio Communication System Yuli Kurnia Ningsih, Syah Alam, Indra Surjati and Marsun	215

Author Index

A. Bayu Primawan, 116 A.S Habibie, 52 Abdillah Fashiha Ilman, 31 Abu Khalid Rivai, 87 Achamd Rizal Danisya, 187, 205 Achmad Syerif Habibie, 46 Adhi Mahendra, 62 Adri Senen, 17 Agung Saputra, 62 Agusutrisno, 87 Ahmad Raditya Cahya Baswara, 74 Alfian Ma'arif, 70, 74, 84, 143 Alfin Hikmaturokhman, 187, 205 Alimuddin, 79 Anang Adi Permana, 149 Andreas P Purnomoadi, 46 Andrie Syatriawan, 41 Anggoro Suryo Pramudyo, 91, 194, 211 Anindita Satria Surya, 46 Aninditya Anggari Nuryono, 74 Anna Nur Nazilah Chamim, 143 Aprilia Kusuma Dewi, 149 Ardiaty Arief, 22 Aulia Nurul Azizah, 158 Azlan Osman, 163 B. B. S. D. A Harsono, 57 Brian Bramantyo SDA Harsono, 46 Ceri Ahendyarti, 97 Chairul Gagarin Irianto, 36 Christine Widyastuti, 17 Citra Nurizati, 91 Damar Widjaja, 179 Dhandis R Jintaka, 57 Dianing Novita Nurmala Putri, 36, 41, 174 Dimaz Damar Wisya Wicaksana, 179 Dzulfiqar Dwi Yanto, 112 Eddie Widiono Suwondo, 41 Edi Suharyadi, 87 Endi Permata, 101 Erlina Erlina, 6 Fadil Muhammad, 97, 112 Fajar Rahayu I. M, 126 Fajardhani, 36 Fauzan Budi Setiawan, 158 Fitri Dwi Kartikasari, 139 Freddy Artadima Silaban, 126 Frengky Panjaitan, 11 Ghina Fahira, 205

Ginas Alvianingsih, 27 Gunady Haryanto, 62 Handrea Bernando Tambunan, 46 Hastuti Aziz, 1 Heri Suyanto, 6, 27 Herudin, 194, 211 Indra Surjati, 183, 215 Irma Saraswati, 91 Ishak Kasim, 41 Iswanto, 70, 74, 84, 107, 143 Iznan H. Hasbullah, 163 Jalu Rinaldi, 143 K. G. H Mangunnkusumo, 57 Kemas M.Tofani, 57 Kornelius Feki Abednego, 121 Lin Prasetyani, 31 Lukman Medriavin Silalahi, 126 Lydia Sari, 183 M. A. Shulhany, 87 M. Herdy Ardiansah, 1 M. Ridwan, 52 Magfirawaty, 149, 158 Mansur Mansur, 22 Mardiyanto, 87 Marsun, 215 Masjudin, 79 Maula Sukma Widjaja, 36 Merlin Oeitheurisa, 139 Mochtar Ali Setyo Yudono, 101 Moh. Jauhari, 31, 163 Muhammad Hafidz, 27 Muhammad Ifan Saputra, 66 Muhammad Iman Santoso, 169 Muhammad Sholeh Masnawan, 70 Muhammad Zainul Arifin, 169 Nazmia Kurniawati, 41, 174 Neneng Rohana, 97 Newton Onasie, 183 Nia Maharani Raharja, 70, 74 Nugroho Adi, 1 Oktaria Handayani, 17 P. A. Permana, 57 P.A.A Pramana, 52 Parminder Singh, 135 Phisca Aditya Rosyady, 74 Priskila Christine Rahayu, 121 Prisma Megantoro, 84, 107 Putu Agus Aditya Pramana, 46

Rai Nur Esa, 187 Rakesh, 183 Ratna Ekawati, 153 Retno Aita Diantari, 6 Ri Munarto, 101 Rian Fahrizal, 163, 169 Riri Fitri Sari, 197 Romi Wiryadinata, 79, 91, 97, 112 Rudy Vernando Silalahi, 121 Ruki Harwahyu, 197 Sabah Benzeghda, 91 Salama Manjang, 22 Selvakumar Manickam, 135 Septi Andryana, 126 Setiyo Budiyanto, 126 Shafiq Ul Rehman, 135, 163 Siti Nur Aisah, 79 Sri Purwiyanti, 66 Sri Ratna Sulistiyanti, 66 Suprihatin, 153

Supriyanto Praptodiyono, 135, 163 Susana Limanto, 139 Syah Alam, 183, 215 Syamsir Abduh, 11, 36, 41 Teguh Firmansyah, 194, 211 Titi Candra Sunarti, 153 Tony Koerniawan, 6 Tresna Dewi, 31 Tyas Kartika Sari, 36 Ucuk Darusalam, 126 Umi Murdika, 66 Vector Anggit Pratomo, 62 Vembi Noverli, 112 Wahyuni Martiningsih, 112 Yandra Arkeman, 153 Yeremia Nikanor Nugroho, 197 Yudhi Ardiyanto, 143 Yuli Kurnia Ningsih, 174, 183, 215 Yusri Syam Akil, 22 Zainal Arifin, 1

Design of Prototype Measuring Motor Vehicles Velocity Using Hall Effect Sensor Series A-1302 based On Arduino Mega2560

¹Muhammad Ifan Saputra Departments of Electrical Engineering Universitas Lampung Bandar Lampung,Indonesia bangipun14@gmail.com ²Sri Ratna Sulistiyanti Departments of Electrical Engineering Universitas Lampung Bandar Lampung,Indonesia sr_sulistiyanti@eng.unila.ac.id

³Sri Purwiyanti Departments of Electrical Engineering Universitas Lampung Bandar Lampung,Indonesia sri.purwiyanti@eng.unila.ac.id

⁴Umi Murdika Departments of Electrical Engineering Univesitas Lampung Bandar Lampung, Indonesia umi.murdika@eng.unila.ac.id

Abstract— This system is designed to get vehicle speed information on the highway. Because the speed of a vehicle on the highway is very influential on other road users. Even based on data taken by the National Police Traffic Corps, speed on vehicles is one of the five violations that are often committed by vehicle users. From this, the authors tried to develop a speed measurement system with the Hall Effect Sensor. The method used in this system is to place two Hall Effect sensors with a certain distance connected to the Arduino Mega2560. When the vehicle passes the first sensor, the timer will start and when the vehicle passes the second sensor, the timer will stop. The results of the construction between the travel time of the vehicle and the distance from the two sensors are what states the speed of a vehicle and will be displayed on the Liquid Crystal Display (LCD) and stored automatically on the SD Card.

Keywords—Hall Effect Sensor, Arduino Mega2560, SD Card.

I. INTRODUCTION

In modern times such as the current motor vehicle has very much experienced development. According to a survey recorded by the Central Statistics Agency in 2016 in Indonesia, there were 129,281,079 motor vehicles while in 2017 there were 138,556,669 which means there was an increase of approximately 9,000,000 motorized vehicles [1]. In fact, according to data taken by the National Police Traffic Corps, speed on motorized vehicles is one of the five violations that are often committed by road users. That led to the idea to make a design and development device prototype measuring motor vehicle velocity using Hall Effect Sensor Series A-1302 based on Arduino Mega2560 [2].

To implement the idea, two Hall Effect Sensors Series A-1302 are needed at a certain distance to get the time difference of the vehicle when it reaches the first Hall Effect Sensor to the second Hall Effect Sensor [3]. The output from the Hall Effect Sensor will be processed by a microcontroller, Arduino Mega2560, where the results of the processing done by Arduino Mega2560 will be displayed on the Liquid Crystal Display (LCD) and stored on the SD Card. When there are vehicles that exceed the preset speed, the Arduino Mega2560 microcontroller will send a short message to the recipient's number with the help of the GSM SIM800L module [4].

The idea was obtained from previous studies, namely research by A. S. Ramdhani entitled Designing a vehicle velocity measurement system using magnetic sensors that get the conclusion that vehicle speed measurements using low input voltage and the distance between two magnetic sensors above 30cm will produce measurements that are optimal [5]. As well as research conducted by A. S. Syifa with the Prototype of vehicle velocity detection with ultrasonic sensor based on Arduino Uno R3which concluded that the prototype was designed to run well and the need for a flat cross-section for this sensor to work optimally [6]. Vehicle speed detection using the ultrasonic principle has been carried out [7, 8] and using the principle of magnetic field detection [9]. However, most of these studies do not detect in real time and no one has done a monitoring system in the form of a warning if a speed limit violation occurs

II. RESEARCH METHOD

In this research, a motorized speed measuring device was designed using Hall Effect Sensor Series A-1302 based on Arduino Mega2560 . The main components of this device consist of Hall Effect Sensor Series A-1302, Arduino Mega2560, Real-Time Clock Type DS1307, GSM800L Module, Shield SD Card Module, LCD 4x20 and also the power supply. This device is designed to measure the speed of motorized vehicles using the Hall Effect Sensor Series A-1302 as a component of its speed gauge, while the 4x20 LCD is used as a viewer of the measurement results in addition to that the measurement results that have been displayed on the 4x20 LCD will be stored in Micro SD Memory as Data Logger. This device is also designed to give a warning in the form of a buzzer and a short message if there are vehicles whose speeds exceed the predetermined limits. The prototype design result could be seen in Figure 1.

When the object measured passes the first Hall Effect Sensor the Timer will be Start and when the object arrives at the second Hall Effect Sensor the Timer will stop. The time difference between Stop and Start will be multiplied by the distance that has been determined, the multiplication process will be carried out by Arduino Mega2560. The results of the processing carried out by Arduino Mega2560 will be displayed on the Liquid Crystal Display (LCD) 4x20 and stored on the SD Card with the help of modules SD Card besides that SD Card will also save the object time passing

Universitas Lampung through DIPA-FT Scheme 2020

through the second Hall Effect Sensor with the help of Real-Time Clock (RTC) DS1307. If there is a vehicle that violates the speed with a predetermined buzzer will sound and the GSM SIM800L module will send a short message to the recipient's cellphone, that there is a speed that exceeds a predetermined limit.



Fig. 1. Prototype of motor vehicle velocity measuring



Fig. 2. Shows the block diagram design of prototype

The functions of the device or components used in this research are as follows:

- Computer Core i3 is used to program the Arduino Mega2560 microcontroller.
- Arduino Mega2560 is used as the main controller for processing design device.
- Hall Effect Sensor Series A-1302 is used as a detector for motorized vehicle whose speed will be measured.
- Liquid Crystal Display (LCD) 4x20 is used as a data viewer that has been processed by Arduino Mega2560.
- The SD Card Module is used to store data that has been processed by the Arduino Mega2560 microcontroller and has been displayed on the LCD.
- Real Time Clock (RTC) DS1307 functions as a date and time display when a vehicle is detected on a device designed and stored on the SD Card.

Converter DC Step Down XL4005 is used to reduce the voltage in accordance with the requirements of the GSM SIM800L Module.

- GSM SIM800L module functions to send a warning if there is a vehicle that is detected violating the speed that should be.
- Buzzer serves as an indicator or reminder if there are vehicles that are detected violating the speed that should be.
- Arduino IDE is used as software to manage the commands that Arduino Mega2560 must do.



Fig. 3. Design of research device

In the prototype design of a vehicle velocity measurement device using the Hall Effect Sensor Series A-1302 (Fig. 3), data collection was carried out by two methods: using a toy car and using a motorized vehicle in actual conditions. Data retrieval in this research was carried out at the Electronic Engineering Laboratory, Integrated Laboratory of Electrical Engineering, the Universitas Lampung. Then the results of the data retrieval will be manually recalculated to ensure that the prototype of a vehicle velocity measurement device using the Hall Effect Sensor Series A-1302 can run well.

In collecting data using a toy car, a 1.2-meter track is used for the toy car to move. Starting from a distance of 10 cm between the two sensors up to 100 cm with a change in the distance between the two sensors is 10 cm per ten data. The toy car is added with a magnet so that the Hall Effect Sensor Series A-1302 can measure the velocity of the toy car (Fig. 4).



Fig. 4. Data Collection Process Using Toy Car

After the toy car passes the second Hall Effect Sensor Series A-1302 series or is set as a time stop, the Arduino Mega2560 microcontroller will process and the results will be displayed on the LCD. If there is a violation, then the buzzer will sound and the GSM SIM800L module will send a message to the destination number. Figure 5 shows the results on the cellphone screen.



Fig. 5. Display Short Message On Recipient's Telephone Number

In collecting data with actual conditions, the object and the distance between the two Hall Effect Sensor Series A-1302 are the differentiators. The Honda Scoopy motorcycle 2019 is used as an object and 5 m is the distance used in collecting data in actual conditions, with velocities ranging from 5 km/h to 8 km/h and each velocity is taken 10 data each (Fig. 6).



Fig. 6. Data Collection Conditions In Actual Conditions

When the overall data collection is needed a tool as a place to put the Hall Effect sensor series A-1302 to detect the magnets on the motorcycle.



Fig. 7. Location of Hall Effect Sensor Series A-1302

From this location the results obtained that the Hall Effect Sensor Series A-1302 is only able to detect magnets that are on the motorcycle with the distance from the sensor to the magnets on the motor is from 5 cm to 15 cm (Fig.7).

Same of taking data on a toy car, when the motorcycle has passed the second Hall Effect Sensor Series A-1302, the

Arduino Mega2560 microcontroller will process then the results will be displayed on the LCD, if there is a violation the buzzer will sound and the GSM SIM800L module will send a message on the recipient's number.

III. RESULT AND DISCUSSION

The first step is to conduct a laboratory-scale trial using a toy car at the distance between the first sensor and the second sensor of 10 cm. The result obtained have an average deviation of 0.0025, an average error value of 0.00003% and an accuracy value of 99.999948%.

The second step is still laboratory scale using toy car with a distance sensor from 10-100 cm. The result obtained an average deviation of 0.0002, an average error value of 0.0000004% and an accuracy value of 99.99996%.

The third step with actual condition at the distance between the first sensor and the second sensor of 5 m. The result obtained have an average deviation of 1.1912, an average error value of 31.47% and an accuracy value of 68.5226%.

The next step with actual condition the velocity of speedometer is 5 km/h—8 km/h. The result obtained an average deviation of 1.4959, an average error value of 31.461875% and an accuracy value of 68.538125%.

In this research, linear regression calculation is done with the equation:

$$y = a + bx \tag{1}$$

The y value is the measured value on the speedometer while the x value is the output value of the designed device. a is a constant and b is a coefficient of the value of the variable x.

So from the equation get the following results (Fig. 8):



Fig. 8. Linier Regression Chart

In addition to using linear regression equations, this research also uses calculations using polynomial regression (Fig. 9). So the results obtained are as follows:

$$y = -0.2157x^2 + 3.2552x - 4.1308 \tag{3}$$



Fig. 9. Polynomial Regression Chart

After getting the correlation equation between the velocity value on the design device and the velocity value on the speedometer, then the value can be used to calculate the velocity value on the design tool by entering Equation 2 or Equation 3 in the program that has been made.

After using linear regression equations get an error of 3.5831% while in the polynomial regression equation get an error of 2.1342%.

After analyzing, there are several factors that influence the level of error value of the measurement data on the design device, factors that affect the error value include the following:

- Wiring between sensors, wiring between sensor one and sensor two is very influential on the accuracy of the data generated by the device that has been designed. Because it is very vulnerable to broken cables or there is an error cable.
- The level of accuracy of the sensor, the level of accuracy of each sensor is different, therefore this is very influential on the data that will be generated by the device that has been designed.

IV. CONCLUSION

After making the design and analysis, it can be concluded that the design and development device prototype measuring motor vehicle velocity using Hall Effect Sensor series a-1302 based on Arduino Mega2560 has been realized. The function of this designed device is to measure the velocity of a motorized vehicle, where velocity data will be stored on the SD card and displayed on a 4 x 20 Liquid Crystal Display (LCD) and when there are vehicles whose speeds exceed the speed they should be, the buzzer will turn on and the GSM SIM800L Module will send a short message with an average error value of 2.1342%.

ACKNOWLEDGMENT

Thank you to the Universitas Lampung who provided funding through Applied Research scheme.

References

- Badan Pusat Satistik." Development of Number of Motorized Vehicles by Type" (Perkembangan Jumlah Kendaraan Bermotor Menurut Jenis), 2017. (Accessed on 30 September 2019). https://www.bps.go.id/linkTableDinamis/view/id/1133.
- [2] D. Pamungkas, "Application of AT89C51 Microcontroller in Vehicle Speed Measurement (Aplikasi Mikrokontroller AT89C51 Pada Pengukuran Kecepatan Kendaraan)". INKOM Jurnal Informatika, Sistem Kendali, dan Komputer, vol. 2, No. 2, pp. 82–88, November 2008.
- [3] Mulyawan, "Vehicle Speed Measurement Design Using ATMEGA32 Microcontroller and Bluetooth Module DBM-01 (Perancangan Alat Pengukur Kecepatan Kendaraan Menggunakan Mikrokontroller ATMEGA32 Dan Modul Bluetooth DBM-01)", Universitas Kristen Maranatha, Bandung.
- [4] A. Nuryaman, E. Mulyana, R. Mardiati, "Designing Prototypes of Vehicle Speed Measuring Devices with Infrared Sensors" (Rancang Bangun Protoipe Alat Pengukur Kecepatan Kendaraan Dengan Sensor Infra Merah). Proceeding Seminar Nasional Teknik Elektro (SENTER), Bandung, 2017, pp. 345–366.
- [5] A.S. Ramdhani, A. Aminudin, A. Danawan. "Designing a vehicle velocity measurement system using magnetic sensors (Rancang Bangun Sistem Pengukur Kecepatan Kendaraan Menggunakan Sensor Magnetik)", Wahana Fisika, vol. 2, No. 1, pp. 29–36, 2017.
- [6] Syifa.Achmad Syariffudin. "Prototype of vehicle velocity detection with ultrasonic sensor based on Arduino Uno R3 (Purwarupa Pendekteksi Kecepatan Kendaraan Dengan Sensor Ultrasonik Berbasis Arduino Uno R3)". Yogyakarta. Universitas Gadjah Mada, 2014.
- [7] Kalyansuriya, S., Eswaran, R.K., Naveen, N., Kumaravel, R., Shanthi, G., "Speed Control of Electric Motor using Ultrasonic Sensor and Image Processing Technique with Raspberry Pi 3", *International Research Journal of Engineering and Technology (IRJET)*, Vol. 06, Issue 01, pp. 1696—1701, 2019.
- [8] Stiawan, R., Kusumadjati, A., Aminah, N.A., Djamal, and M., Viridi, S., "An Ultrasonic Sensor System for Vehicle Detection Application", *IOP Conf. Series: Journal of Physics: Conf. Series*, Vol. 1204, pp.1— 6, 2019.
- [9] Markevicius, V., Navikas, D., Zilys, M., Andriukaitis, D., Valinevicius, A., and Cepenas, M.," Dynamic Vehicle Detection via the Use of Magnetic Field Sensors", *Sensors*, Vol. 16, pp.1–9, 2016.



2nd International Conference on Industrial Electrical and Electronics Electrical Engineering Department – University of Sultan Ageng Tirtayasa http://iciee.untirta.ac.id/email : iciee@untirta.ac.id Mobile : +62 813 6767 4213

Cilegon, September, 30th, 2020.

Dear Authors:

Muhammad Ifan Saputra, Sri Ratna Sulistiyanti, Sri Purwiyanti, and Umi Murdika

We are pleased to inform you that your Full Paper (FP#32), entitled:

"Design of Prototype Measuring Motor Vehicles Velocity Using Hall Effect Sensor Series A-1302 based On Arduino Mega2560"

has been reviewed and **accepted** to be presented at ICIEE 2020 conference to be held on October, $20 - 21^{\text{th}}$, 2020 Virtually.

Please make the payment for **registration fee** before the deadlines, visit our website (<u>http://iciee.untirta.ac.id</u>) for more information.

Thank You.

Best Regards,

Anggoro Suryo Pramudyo, M.Kom.

ICIEE 2020 Chairperson

IEEE COPYRIGHT AND CONSENT FORM

To ensure uniformity of treatment among all contributors, other forms may not be substituted for this form, nor may any wording of the form be changed. This form is intended for original material submitted to the IEEE and must accompany any such material in order to be published by the IEEE. Please read the form carefully and keep a copy for your files.

Design of Prototype Measuring Motor Vehicles Velocity Using Hall Effect Sensor Series A-1302 Based On Arduino Mega2560 Muhammad Ifan Saputra, Sri Ratna Sulistiyanti, Sri Purwiyanti and Umi Murdika 2020 2nd International Conference on Industrial Electrical and Electronics (ICIEE)

COPYRIGHT TRANSFER

The undersigned hereby assigns to The Institute of Electrical and Electronics Engineers, Incorporated (the "IEEE") all rights under copyright that may exist in and to: (a) the Work, including any revised or expanded derivative works submitted to the IEEE by the undersigned based on the Work; and (b) any associated written or multimedia components or other enhancements accompanying the Work.

GENERAL TERMS

- 1. The undersigned represents that he/she has the power and authority to make and execute this form.
- 2. The undersigned agrees to indemnify and hold harmless the IEEE from any damage or expense that may arise in the event of a breach of any of the warranties set forth above.
- 3. The undersigned agrees that publication with IEEE is subject to the policies and procedures of the <u>IEEE PSPB</u> <u>Operations Manual</u>.
- 4. In the event the above work is not accepted and published by the IEEE or is withdrawn by the author(s) before acceptance by the IEEE, the foregoing copyright transfer shall be null and void. In this case, IEEE will retain a copy of the manuscript for internal administrative/record-keeping purposes.
- 5. For jointly authored Works, all joint authors should sign, or one of the authors should sign as authorized agent for the others.
- 6. The author hereby warrants that the Work and Presentation (collectively, the "Materials") are original and that he/she is the author of the Materials. To the extent the Materials incorporate text passages, figures, data or other material from the works of others, the author has obtained any necessary permissions. Where necessary, the author has obtained all third party permissions and consents to grant the license above and has provided copies of such permissions and consents to IEEE

You have indicated that you DO wish to have video/audio recordings made of your conference presentation under terms and conditions set forth in "Consent and Release."

CONSENT AND RELEASE

- 1. In the event the author makes a presentation based upon the Work at a conference hosted or sponsored in whole or in part by the IEEE, the author, in consideration for his/her participation in the conference, hereby grants the IEEE the unlimited, worldwide, irrevocable permission to use, distribute, publish, license, exhibit, record, digitize, broadcast, reproduce and archive, in any format or medium, whether now known or hereafter developed: (a) his/her presentation and comments at the conference; (b) any written materials or multimedia files used in connection with his/her presentation; and (c) any recorded interviews of him/her (collectively, the "Presentation"). The permission granted includes the transcription and reproduction of the Presentation for inclusion in products sold or distributed by IEEE and live or recorded broadcast of the Presentation during or after the conference.
- 2. In connection with the permission granted in Section 1, the author hereby grants IEEE the unlimited, worldwide, irrevocable right to use his/her name, picture, likeness, voice and biographical information as part of the advertisement, distribution and sale of products incorporating the Work or Presentation, and releases IEEE from any claim based on right of privacy or publicity.

BY TYPING IN YOUR FULL NAME BELOW AND CLICKING THE SUBMIT BUTTON, YOU CERTIFY THAT SUCH ACTION CONSTITUTES YOUR ELECTRONIC SIGNATURE TO THIS FORM IN ACCORDANCE WITH UNITED STATES LAW, WHICH AUTHORIZES ELECTRONIC SIGNATURE BY AUTHENTICATED REQUEST FROM A USER OVER THE INTERNET AS A VALID SUBSTITUTE FOR A WRITTEN SIGNATURE.

Sri Ratna Sulistiyanti

Signature

09-10-2020

Date (dd-mm-yyyy)

Information for Authors

AUTHOR RESPONSIBILITIES

The IEEE distributes its technical publications throughout the world and wants to ensure that the material submitted to its publications is properly available to the readership of those publications. Authors must ensure that their Work meets the requirements as stated in section 8.2.1 of the IEEE PSPB Operations Manual, including provisions covering originality, authorship, author responsibilities and author misconduct. More information on IEEE's publishing policies may be found at http://www.ieee.org/publications_standards/publications/rights/authorrightsresponsibilities.html Authors are advised especially of IEEE PSPB Operations Manual section 8.2.1.B12: "It is the responsibility of the authors, not the IEEE, to determine whether disclosure of their material requires the prior consent of other parties and, if so, to obtain it." Authors are also advised of IEEE PSPB Operations Manual section 8.1.1B: "Statements and opinions given in work published by the IEEE are the expression of the authors."

RETAINED RIGHTS/TERMS AND CONDITIONS

- Authors/employers retain all proprietary rights in any process, procedure, or article of manufacture described in the Work.
- Authors/employers may reproduce or authorize others to reproduce the Work, material extracted verbatim from the Work, or derivative works for the author's personal use or for company use, provided that the source and the IEEE copyright notice are indicated, the copies are not used in any way that implies IEEE endorsement of a product or service of any employer, and the copies themselves are not offered for sale.
- Although authors are permitted to re-use all or portions of the Work in other works, this does not include granting third-party requests for reprinting, republishing, or other types of re-use. The IEEE Intellectual Property Rights office must handle all such third-party requests.
- Authors whose work was performed under a grant from a government funding agency are free to fulfill any deposit mandates from that funding agency.

AUTHOR ONLINE USE

- **Personal Servers**. Authors and/or their employers shall have the right to post the accepted version of IEEE-copyrighted articles on their own personal servers or the servers of their institutions or employers without permission from IEEE, provided that the posted version includes a prominently displayed IEEE copyright notice and, when published, a full citation to the original IEEE publication, including a link to the article abstract in IEEE Xplore. Authors shall not post the final, published versions of their papers.
- **Classroom or Internal Training Use.** An author is expressly permitted to post any portion of the accepted version of his/her own IEEE-copyrighted articles on the author's personal web site or the servers of the author's institution or company in connection with the author's teaching, training, or work responsibilities, provided that the appropriate copyright, credit, and reuse notices appear prominently with the posted material. Examples of permitted uses are lecture materials, course packs, e-reserves, conference presentations, or in-house training courses.
- Electronic Preprints. Before submitting an article to an IEEE publication, authors frequently post their manuscripts to their own web site, their employer's site, or to another server that invites constructive comment from colleagues. Upon submission of an article to IEEE, an author is required to transfer copyright in the article to IEEE, and the author must update any previously posted version of the article with a prominently displayed IEEE copyright notice. Upon publication of an article by the IEEE, the author must replace any previously posted electronic versions of the article with either (1) the full citation to the

IEEE work with a Digital Object Identifier (DOI) or link to the article abstract in IEEE Xplore, or (2) the accepted version only (not the IEEE-published version), including the IEEE copyright notice and full citation, with a link to the final, published article in IEEE Xplore.

Questions about the submission of the form or manuscript must be sent to the publication's editor. Please direct all questions about IEEE copyright policy to: IEEE Intellectual Property Rights Office, copyrights@ieee.org, +1-732-562-3966



International Conference on Industrial Electrical and Electronics

Virtual Conference (October 20-21, 2020)



Registration Fee for Presenter

International Presenter	Student	Regular	IEEE Member
Early Bird	USD 300	USD 400	USD 350
	USD 200	USD 300	USD 250
Regular	USD 350	USD 450	USD 400
	USD 250	USD 350	USD 300

Domestic/Local Presenter	Student	Regular	IEEE/FORTEI Member
Early Bird	IDR 2.500.000	IDR 3.500.000	IDR 3.000.000
	IDR 1.500.000	IDR 2.500.000	IDR 2.000.000
Regular	IDR 3.000.000	IDR 4.000.000	IDR 3.500.000
	IDR 2.000.000	IDR 3.000.000	IDR 2.500.000

The page limit for regular (full) is six (6) pages. Please note that extra pages will be charged USD 20 (or IDR 200.000 for local presenter) per page.

Registration Fee for Participant

Participant	Domestic/Local	International
Student/Regular	IDR 1.000.000	USD 150

Registration Form for Participant (https://forms.gle/dYKVg1GjZrrgKeZQA)

Last Payment for Phase 1 is 5th July 2018 Last Payment for Phase 2 is 6th August 2018

*/ ?>

Registration fees for presenter or participant are transferred to the account:

Bank Negara Indonesia (Serang Branch)Swift Code: BNINIDJASRGAccount Number: 988 60609 21 000001Account Name: Seminar Fakultas TeknikTreasurer: Ceri Ahendyarti

if you need Beneficiary ID of the Treasurer, please contact us: ICIEE Organizing Committe Email : iciee@untirta.ac.id Mobile/Whats-App: +62 81367674213

Tentative Agenda

Tentative Agenda (ICIEE 2020 Tentative Agenda.pdf)

Main Room (room) Room01 (room01) Room02 (room02) Room03 (room03) Room04 (room04)

Paper Submission



(https://easychair.org/conferences/?conf=iciee2020)

Template (conference-template-a4.docx) Submission (https://easychair.org/conferences/?conf=iciee2020)

Author Guidelines (icieeauthorguidance.pdf)

Important Dates

Phase 1 Full Paper Submission Deadline February 5, 2020 February 20, 2020 Notification March 5, 2020

Phase 2 Full Paper Submission Deadline March 5, 2020 March 15, 2020 April 1, 2020 11/10/2020

July 15, 2020 **Notification** March 20, 2020 April 10, 2020 August 15, 2020

Camera Ready April 5, 2020 September 20, 2020 Early Bird Registration September 10, 2020 Conferences Date October 20-21, 2020

Conference Day

October 20-21th, 2020

Virtual Conference using Webex Event Platform

Organized By



(http://elektro.untirta.ac.id)

Electrical Engineering Department Universitas Sultan Ageng Tirtayasa (http://elektro.untirta.ac.id)

Supported By







(http://icefory.untirta.ac.id/)

Technical Co Sponsor

ICIEE 2020



(https://ieee.id/)



(http://s11.flagcounter.com/more/sO8O)

ICIEE Organizing Committe Email : iciee@untirta.ac.id Mobile : +6281367674213 © 2020 Electrical Engineering Department

Jl. Jend. Sudirman km.3, Cilegon, Indonesia 42435 Universitas Sultan Ageng Tirtayasa





The 2nd International Conference on Industrial Electrical and Electronics (ICIEE)

Certificate of appreciation is proudly awarded to :

MUHAMMAD IFAN S

In recognition and appreciation of your contribution as

Paper ID 032 Entitled: Design of Prototype Measuring Motor Vehicles Velocity Using Hall Effect Sensor Series A-1302 Based on Arduino Mega2560



Organizer:



Supported by:







PUL - P

Assoc. Prof. Dr. Ir. Supriyanto, M.Sc., IPM.

General Chair